




Product Selection

10 kAIC, 120 Vac, 120/240 Vac and 240 Vac

Type CH Plug-On Circuit Breakers





Type CH Breakers, 3/4-Inch (19.1 mm) per Pole 120, 120/240 or 240 Vac, 10 kAIC

| Ampere Rating | Wire Size Range Cu/Al 60°C or 75°C | Catalog Number | | |
|---------------|------------------------------------|--|--|--|
| | | Single-Pole 120/240 Vac Requires One 3/4-Inch (19.1 mm) Space 10 per Shelf Carton | Two-Pole 120/240 Vac Common Trip Requires Two 3/4-Inch (19.1 mm) Spaces 5 per Shelf Carton | Three-Pole 240 Vac Common Trip Requires Three 3/4-Inch (19.1 mm) Spaces 5 per Shelf Carton |
| 10 | (1) #14-8 ① |  CH110 |  CH210 |  CH310 |
| 15 | (2) #14-10 ①② (1) #14-6 ③ | CH115 ⑦⑧ | CH215 ⑧ | CH315 ⑧ |
| 20 | | CH120 ⑦⑧ | CH220 ⑧ | CH320 ⑧ |
| 25 | | CH125 ⑧ | CH225 ⑧ | CH325 ⑧ |
| 30 | | CH130 ⑧ | CH230 ⑧ | CH330 ⑧ |
| 35 | #14-2 ① #14-6 ③ | CH135 ⑧ | CH235 ⑧ | CH335 ⑧ |
| 40 | #10-1/0 ④ | CH140 ⑧ | CH240 ⑧ | CH340 ⑧ |
| 45 | #14-2 ⑤ #3/0 ⑥ | CH145 ⑧ | CH245 ⑧ | CH345 ⑧ |
| 50 | | CH150 ⑧ | CH250 ⑧ | CH350 ⑧ |
| 60 | | CH160 | CH260 | CH360 |
| 70 | | CH170 | CH270 | CH370 |
| 80 | | — | CH280 | CH3080 |
| 90 | | — | CH290 | CH3090 |
| 100 | | — | CH2100 | CH3100 |
| 110 | | — | CH2110 | — |
| 125 | | — | CH2125 | — |

Type CH Plug-On Circuit Breakers



CHF Breakers with Mechanical Trip Flag

| Ampere Rating | Wire Size Range Cu/Al 60°C or 75°C | Catalog Number | |
|---------------|------------------------------------|---|---|
| | | Single-Pole 120/240 Vac Requires One 3/4-Inch (19.1 mm) Space 10 per Shelf Carton | Two-Pole 120/240 Vac Common Trip Requires Two 3/4-Inch (19.1 mm) Spaces 5 per Shelf Carton |
| 10 | (1) #14-8 ① |  CHF110 |  CHF210 |
| 15 | (2) #14-10 ①② | CHF115 ⑦⑧ | CHF215 ⑧ |
| 20 | | CHF120 ⑦⑧ | CHF220 ⑧ |
| 25 | | CHF125 ⑧ | CHF225 ⑧ |
| 30 | | CHF130 ⑧ | CHF230 ⑧ |
| 35 | #14-2 ① | CHF135 ⑧ | CHF235 ⑧ |
| 40 | #10-1/0 ④ | CHF140 ⑧ | CHF240 ⑧ |
| 45 | #14-2 ⑤ | CHF145 ⑧ | CHF245 ⑧ |
| 50 | | CHF150 ⑧ | CHF250 ⑧ |

Notes

- ① For single- and two-pole breakers.
- ② Solid and stranded wire can be used together.
- ③ For three-pole breakers.
- ④ Single-pole 60-70A, two-pole 80-125A, three-pole 40-100A.
- ⑤ Single-pole 40-50A, two-pole 40-70A.
- ⑥ Two-pole 150A.
- ⑦ Switching duty rated.
- ⑧ HACR rated.

For factory-installed options, refer to **Page V1-T1-39**.